

Appl. No. 10/556,647
Amdt. A dated March 25, 2008
Reply to O.A. of September 26, 2008

RECEIVED
CENTRAL FAX CENTER

PATENT
Docket No. 28944/40163

MAR 25 2008

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application.

1. (currently amended) Voltage shift control circuit intended to be placed in parallel with at least one series voltage shift capacitor coupling the phase comparator and the voltage controlled oscillator of a phase locked loop and comprising:

- an input, intended to be coupled with the output of the phase comparator;
- an output, intended to be coupled with the input of the voltage controlled oscillator;
- controlled charging means, designed to charge the voltage shift capacitor according to a control signal;
- controlled pre-charging means, designed to accelerate the charging of the voltage shift capacitor by the controlled charging means; and
- controlled polarization means, designed to ensure the polarization of the input during the pre-charging of the voltage shift capacitor.

2. (previously presented) Circuit according to Claim 1, wherein the controlled charging means comprise a first operational amplifier connected as a voltage follower between the input and the output, a resistor placed in the feedback loop of the operational amplifier, and a controlled current source supplying a current of specified value through said resistor.

3. (previously presented) Circuit according to Claim 2, wherein the operational amplifier of the charging means comprise a push-pull output stage, and wherein the charging means further comprise a resistor of high value connected in series between the output of the operational amplifier and the output of the circuit.

4. (previously presented) Circuit according to Claim 3, wherein the controlled pre-charging means comprise a push-pull stage which, in the activation of the pre-charging means configuration,

Appl. No. 10/556,647
Amdt. A dated March 25, 2008
Reply to O.A. of September 26, 2008

PATENT
Docket No. 28944/40163

is arranged as a mirror with respect to the push-pull output stage of the operational amplifier of the charging means, in such a way as to short-circuit the high value resistor.

5. (original) Circuit according to Claim 4, wherein the push-pull stage of the pre-charging means is designed to deliver a current higher than the current delivered by the push-pull output stage of the operational amplifier of the charging means.

6. (previously previously) Circuit according to Claim 1, wherein the controlled polarization means comprise a second operational amplifier connected as a voltage follower which, in the activation of the controlled polarization means configuration, is arranged to impose a common mode voltage on the input of the circuit.

7. (previously presented) Circuit according to Claim 1, further comprising means for deactivating the controlled pre-charging means before the controlled polarization means.

8. (previously presented) Circuit according to Claim 2, further comprising an additional controlled push-pull stage whose output is intended to be connected to the centre point of an RC network of a loop filter of the PLL and which, in the activation configuration, is connected as a mirror with respect to the push-pull stage of the controlled pre-charging means and with respect to the push-pull output stage of the operational amplifier of the charging means.

9. (original) Circuit according to Claim 8, wherein the additional controlled push-pull stage is integrated with the operational amplifier of the charging means.

10. (previously presented) Circuit according to Claim 1, designed in CMOS technology.

11. (currently amended) Phase locked loop comprising a phase or frequency comparator, a loop filter, a voltage controlled oscillator, a series voltage shift capacitor connecting the phase

Appl. No. 10/556,647
Amdt. A dated March 25, 2008
Reply to O.A. of September 26, 2008

PATENT
Docket No. 28944/40163

comparator and the voltage controlled oscillator, and a voltage shift control circuit according to Claim 1 placed in parallel with the series voltage shift capacitor and comprising:

- an input, intended to be coupled with the output of the phase comparator;
- an output, intended to be coupled with the input of the voltage controlled oscillator;
- controlled charging means, designed to charge the voltage shift capacitor according to a control signal;
- controlled pre-charging means, designed to accelerate the charging of the voltage shift capacitor by the controlled charging means; and
- controlled polarization means, designed to ensure the polarization of the input during the pre-charging of the voltage shift capacitor.

12. (currently amended) Radio-frequency transmitter, having a phase locked loop for generating a radio-frequency signal to be transmitted, said phase locked loop comprising a phase or frequency comparator, a loop filter, a voltage controlled oscillator, a series voltage shift capacitor connecting the phase comparator and the voltage controlled oscillator, and a voltage shift control circuit according to Claim 1 placed in parallel with the series voltage shift capacitor and comprising:

- an input, intended to be coupled with the output of the phase comparator;
- an output, intended to be coupled with the input of the voltage controlled oscillator;
- controlled charging means, designed to charge the voltage shift capacitor according to a control signal;
- controlled pre-charging means, designed to accelerate the charging of the voltage shift capacitor by the controlled charging means; and
- controlled polarization means, designed to ensure the polarization of the input during the pre-charging of the voltage shift capacitor.

13. (currently amended) Mobile terminal of a radio-communications system with a radio-frequency transmitter having a phase locked loop for generating a radio-frequency signal to be transmitted, said phase locked loop comprising a phase or frequency comparator, a loop filter, a

Appl. No. 10/556,647
Amdt. A dated March 25, 2008
Reply to O.A. of September 26, 2008

PATENT
Docket No. 28944/40163

voltage controlled oscillator, a series voltage shift capacitor connecting the phase comparator and the voltage controlled oscillator, and a voltage shift control circuit according to claim 1 placed in parallel with the series voltage shift capacitor and comprising:

- an input, intended to be coupled with the output of the phase comparator;
- an output, intended to be coupled with the input of the voltage controlled oscillator;
- controlled charging means, designed to charge the voltage shift capacitor according to a control signal;
- controlled pre-charging means, designed to accelerate the charging of the voltage shift capacitor by the controlled charging means; and
- controlled polarization means, designed to ensure the polarization of the input during the pre-charging of the voltage shift capacitor.

14. (currently amended) Base station of a radio-communications system with a radio-frequency transmitter having a phase locked loop for generating a radio-frequency signal to be transmitted, said phase locked loop comprising a phase or frequency comparator, a loop filter, a voltage controlled oscillator, a voltage shift capacitor connecting the phase comparator and the voltage controlled oscillator, and a series voltage shift control circuit according to Claim 1 placed in parallel with series the voltage shift capacitor and comprising:

- an input, intended to be coupled with the output of the phase comparator;
- an output, intended to be coupled with the input of the voltage controlled oscillator;
- controlled charging means, designed to charge the voltage shift capacitor according to a control signal;
- controlled pre-charging means, designed to accelerate the charging of the voltage shift capacitor by the controlled charging means; and
- controlled polarization means, designed to ensure the polarization of the input during the pre-charging of the voltage shift capacitor.